

Anlage 1

**Übersicht der BOS-Frequenzen im Bereich
165,210 MHz bis 173,980 MHz**

Kanal	Frequenzpaar MHz	Kanal	Frequenzpaar MHz	Kanal	Frequenzpaar MHz
101	165,210/169,810	15	167,840/172,440	55	168,640/173,240*
102	165,230/169,830	16	167,860/172,460	56	168,660/173,260*
103	165,250/169,850	17	167,880/172,480	57	168,680/173,280
104	165,270/169,870	18	167,900/172,500	58	168,700/173,300
105	165,290/169,890	19	167,920/172,520	59	168,720/173,320
106	165,310/169,910	20	167,940/172,540	60	168,740/173,340
107	165,330/169,930	21	167,960/172,560	61	168,760/173,360
108	165,350/169,950	22	167,980/172,580	62	168,780/173,380
109	165,370/169,970	23	168,000/172,600	63	168,800/173,400
110	165,390/169,990	24	168,020/172,620	64	168,820/173,420
111	165,410/170,010	25	168,040/172,640	65	168,840/173,440
112	165,430/170,030	26	168,060/172,660	66	168,860/173,460
113	165,450/170,050	27	168,080/172,680	67	168,880/173,480
114	165,470/170,070	28	168,100/172,700	68	168,900/173,500
115	165,490/170,090	29	168,120/172,720	69	168,920/173,520
116	165,510/170,110	30	168,140/172,740	70	168,940/173,540
117	165,530/170,130	31	168,160/172,760	71	168,960/173,560
118	165,550/170,150	32	168,180/172,780	72	168,980/173,580
119	165,570/170,170	33	168,200/172,800	73	169,000/173,600
120	165,590/170,190	34	168,220/172,820	74	169,020/173,620
121	165,610/170,210	35	168,240/172,840	75	169,040/173,640
122	165,630/170,230	36	168,260/172,860	76	169,060/173,660
123	165,650/170,250	37	168,280/172,880	77	169,080/173,680
124	165,670/170,270	38	168,300/172,900	78	169,100/173,700
125	165,690/170,290	39	168,320/172,920	79	169,120/173,720
		40	168,340/172,940	80	169,140/173,740
01	167,560/172,160	41	168,360/172,960	81	169,160/173,760
02	167,580/172,180	42	168,380/172,980	82	169,180/173,780
03	167,600/172,200	43	168,400/173,000	83	169,200/173,800
04	167,620/172,220	44	168,420/173,020	84	169,220/173,820
05	167,640/172,240	45	168,440/173,040	85	169,240/173,840
06	167,660/172,260	46	168,460/173,060	86	169,260/173,860
07	167,680/172,280	47	168,480/173,080	87	169,280/173,880
08	167,700/172,300	48	168,500/173,100	88	169,300/173,900
09	167,720/172,320	49	168,520/173,120	89	169,320/173,920
10	167,740/172,340	50	168,540/173,140*	90	169,340/173,940
11	167,760/172,360	51	168,560/173,160	91	169,360/173,960
12	167,780/172,380	52	168,580/173,180	92	169,380/173,980
13	167,800/172,400	53	168,600/173,200*		
14	167,820/172,420	54	168,620/173,220		

Vorzugsweise werden die mit * gekennzeichneten Oberband-Frequenzen bundesweit für die Digitale Alarmierung eingesetzt