

Anlage 3
VS-Nur für den Dienstgebrauch

Frequenzübersicht - 8 m-Bereich

Kanal	Frequenz oder Frequenzpaar in MHz	Kanal	Frequenz oder Frequenzpaar in MHz
801 -	34,360/38,460	841 -	39,260
802 -	34,380/38,480	842 -	39,280
803 -	34,400/38,500	843 -	39,300
804 -	34,420/38,520	844 -	35,220/39,320
805 -	34,440/38,540	845 -	35,240/39,340
806 -	34,460/38,560	846 -	35,260/39,360
807 -	34,480/38,580	847 -	35,280/39,380
808 -	34,500/38,600	848 -	35,300/39,400
809 -	34,520/38,620	849 -	35,320/39,420
	Kanäle 810-820 an BMVg abgege- ben	850 -	35,340/39,440
821 -	38,860	851 -	35,360/39,460
822 -	38,880	852 -	35,380/39,480
823 -	38,900	853 -	35,400/39,500
824 -	38,920	854 -	35,420/39,520
825 -	38,940	855 -	35,440/39,540
826 -	38,960	856 -	35,460/39,560
827 -	38,980	857 -	35,480/39,580
		858 -	35,500/39,600
	Kanäle 828-831 an RegTP abge- geben	859 -	35,520/39,620
		860 -	35,540/39,640
		861 -	35,560/39,660
832 -	34,980/39,080	862 -	35,580/39,680
833 -	39,100	863 -	35,600/39,700
834 -	39,120	864 -	35,620/39,720
835 -	39,140	865 -	35,640/39,740
836 -	39,160	866 -	35,660/39,760
837 -	39,180	867 -	35,680/39,780
838 -	39,200	868 -	35,700/39,800
839 -	39,220	869 -	35,720/39,820
840 -	39,240	870 -	35,740/39,840
		871 -	35,760
		872 -	35,780
		873 -	35,800